

Low-power Keypad C1000LP

Art. No.: 480005 (black), 480006 (white)

User Manual



CE



Table of Content

1.	Introduction	page 3
2.	Installation	page 3
3.	Programming users	page 4
3.1	User positions	page 4
3.2	Programming user codes	page 4
3.3	Programming user codes on special positions	page 5
3.4	Smart enrolling	page 6
4.	Battery Management	page 6-7
5.	Configuring C1000LP	
5.1	Service code	page 8
5.2	Configuration overview	page 8
5.3	Changing Master Code	page 8
5.4	Changing Service Code	page 9
5.5	LED Indications	page 9
5.6	Output setup	page 10
5.7	Special settings	page 11
6.	Blocking (Duress)	page 12
7.	Manual reset	page 12
8.	Technical specifications	page 12
9.	One-time/day code	page 13
10.	Free locker	page 14



1. Introduction

C1000LP is a low power keypad that works on electronic locks with open collector and/or H-Bridge mode.

In standby mode the yellow LED is lit (● ○ ○)

By correct code lights yellow and green LED (● ● ○)

By incorrect code lights the red LED (○ ○ ●)


C1000LP has a buzzer for indicating while keying, correct code, incorrect etc. and 2 transistor outputs, independent from each other, so the C1000LP can give access by code.

The C1000LP is a stand alone unit, it can be programmed directly by Master code and Service code.

2. Installation

Mount the reader on an even surface.

Connect the wires to power supply, door strike etc. (use supplied diode)



Note: Right after applying the voltage all LED's lights and the buzzer sounds **do not** touch the reader until the yellow LED lights and the buzzer is silent.



3. Programming users

Programming the C1000LP is simple and easy to understand.

3.1 User positions

C1000LP has 200 user positions, which can contain a code. The positions are divided as following:


User position	Function
1 - 100	Activates output 2 (The code is position 1 is 1234 - factory default)
101 - 150	Activates output 1
151 - 190	Activates output 1 and 2
191 - 200	Reserved for special functions


3.2 Programming user codes

The Master code is used to program/change/delete the users. By default the Master code is **4711**.

LED indication: No light: ○ Lit: ● Flash: ✱ Clear buffer: 

New users




To program more users, continue from “Key in the user position” or press  to exit.

Changing codes


It's the same procedure as programming new users, just overwrite the user position.



Delete specific users



Delete all users



3.3 Programming codes for special functions

Programming the codes is described in 3.2 and 3.3. This entry activates the output(s) for 5 seconds (factory setting). Only 1 user can enter at the time.

Programming the same user twice

By programming the same code on the same position twice toggles the output. (I.e. the code is entered to unlock the door and entered to lock it again).

Programming the same user 3 times

By programming the same code on the same position 3 times, the output is designated as switch on only. (I.e. the door is permanently unlocked when the code is entered).


Programming the same user 4 times

By programming the same code on the same position 4 times, the output is designated as switch off only. (I.e. the door is only locked when the code is entered).



3.4 Smart enrolling

This position makes it possible to program codes quicker without entering new positions. Key in a position and it counts automatically to the next position. Codes can be programmed alternatively as you see fit.




Note: This programming mode overwrites existing positions.

4. Battery management


Gives a warning before opening the door, when the battery is at approx 10% charge.

Preset Battery low warning (1#):

Position	Select chemistry	Series cell count
0	Disable	
1	Alkaline 1,5V	(0,95V) 3-10 cells
2	Lithium 3V	(2,3V) 1-5 cells
3	Li-poly/Li-ion 3, 7V	(3,37V) 1-4 cells
4	Lead Acid 2, 1V	(1,95V) 2-7 cells




Here is an example of how you preset the battery when having a 12V Lead Acid with 6 cells. See following instructions.






Custom battery low warning (2#):

If you do not have any of the mentioned battery types, you can customize your battery size. See following instructions.



Here is an example of how you preset the customized battery low warning. In this example we want the battery to send a warning at 10,8V.



When the battery is running low it will give you a warning when you type in your user code. The red LED will flash while the buzzer beeps for about 3 seconds. The output is hereafter activated.



5. Configuration of C1000LP

5.1 The Service code

The Service code is used for C1000LP's advanced settings such as changing the Master code and Service code, LED indications and much more. The overview of the settings and the factory settings can be seen in 4.2 *Configuration overview*.

The Service code is **12347890** (factory setting).

Note: Before the Service code can be used must the voltage be turned OFF and ON (the Service code can now be entered within 10 seconds).

After entering the Service code the reader is in programming mode (the green LED lights). Each time a setting is made the C1000LP goes back to the previous point and the next setting can be made.

The navigation is by entering the position/ value followed by #.

5.2 Configuration overview

Position	Setting	Factory default
00	Master code (1 to 8 digits)	4711
01	Service code (1 to 8 digits)	12347890
02	LED indications	Normal = Yellow, active = Yellow and green
03	Output setup	Output time for 1 and 2 is 5 seconds
04	Special functions	
05	Smart enrolling	
06	Input setup	
07	Time	
08	Battery management	
09	Locker reserve time	
2500	All codes on the user positions are deleted	
0250	Reset to factory default	

5.3 Changing the Master code

By default the Master code is **4711** and can only be used to program, change or delete users on the C1000LP. To change the Master code, enter the following:






5.4 Changing the Service code

The Service code is used to configure the C1000LP's settings.



To change the Service code, enter the following within 10 seconds after power on:




5.5 LED indications

The C1000LP's 3 LED's can be adjusted at will.


To adjust the LED indications enter the following:



adjust the LED's for standby indication (normal).



adjust the LED's for correct code indication (active).



adjust the keying indication (how the LED will react while keying).

To adjust the LED's press on the following:

1 = yellow LED (toggle by press)

2 = green LED (toggle by press)

3 = red LED (toggle by press)

0 = buzzer (works only on active and keying indication (toggle by press))

= save and go one step back


To save the settings press # or press * to go back to the previous point (not saving).



5.6 Output setup

The C1000LP has 2 outputs that can be set to H-Bridge output or open collector output. By default is the C1000LP set to H-Bridge output with Lock delay in 5 seconds.

To configure the output settings use the following steps:



- 1 sets the output 1 time in Pulse mode or Lock delay
- 2 sets the output 2 time in Pulse mode or H-Bridge time
- 3 sets the output 1 active position
- 4 sets the output 2 active position
- 5 sets the output functions
- 6 select the outputs for Daycode/onetime code

Please use the configuration scheme under "03" section for correct navigation for OC setup

Note: In time setting for Pulse mode it is in Milisec x 10 instead of hours.



5.7 Special settings

These settings is used to change the C1000LP's special functions such as turning the buzzer on/off etc.

To change these settings, key in: 04 → #
●○○

- 1 = Service code without timeout (● = inactive / ● = active)
- 2 = Master code be changed by Master code (● = inactive / ● = active)
- 3 = Mute reader (● = Off / ● = On)
- 4 = Bell on OC1 (● = Off / ● = On)
- 5 = Onetime code (● = Off / ● = On)
- 6 = Day code (● = Off / ● = On)
- 7 = Locker mode (● = Off / ● = On)
- 8 = Free locker mode (● = Off / ● = On)

Special positions

User position 191 to 197 can activate special setting 3 to 6 with a code. The programming is the same procedure as programming a user code just use the positions mentioned below:

- 191 = Toggle buzzer
- 193 = Reset of free locker
- 194 = Toggling the star key to activate output 1 (white wire)
- 195 = Toggle onetime code mode
- 196 = Toggle Daycode mode
- 197 = Deactivate the user codes
- 198 = Seed code
- 199 = Digit count for one/day code

To save the settings press # or press * to go back to the previous step (no saving).

Note: In case of power disruption the special functions will go back to the setup made by service code.



6. Blocking

The C1000LP is blocked for 1 minute after 4 incorrect codes.

LED indication: ○○●

7. Manual reset

The C1000LP can be reset to factory default manually.

- Turn the voltage off.
- Connect the yellow and brown wire.
- Turn the voltage on (2 - 16 V DC) the readers LED's lights and the buzzer sounds.
- Turn the voltage off and disconnect the yellow and brown wire.

The C1000LP is now reset to factory default and the user codes are deleted.

8. Technical specifications

Voltage range:	2 - 16V DC
Mifare reading:	Max. 50 mm
Output:	2x open collector, max. 500mA
Input:	External buzzer/Feedback (brown) and REX, 0V active (blue)
Protection rate:	IP67
Color:	Black or white
Cable:	2,5 meter white, 8 cores
Dimensions (HxBxD):	130x50x8 mm



9. One-time-/day code


The C1000LP offers 2 advanced functions of codes that can be used once only and a code that is valid for a single day.

First the codes have to be generated using the ConlanCode Generator (download available from www.conlan.eu or on itunes and Google Play).



Enter a seed number into the first box. This can be any number from 1 to 9999999. Then enter the numbers of digits you require the code to have (best to avoid 4 or 8 digits codes so there is no chance of conflict with Service code or Master code. The system defaults to a 6 digit code.

Once you press the enter key, the day code will be shown on the left and a series of one-time codes shown in the table below. Both these can be exported to a file if required.

Conlan Code Generator for Windows, for administration of one-time and day codes.




Conlan Day Code app for iOS and Android units for administration of day codes with SMS and Email notification.




When the information is specified, the C1000LP can be set:

Setting the time



Activation of One-time-/day code



Finally, the reader must know how many digits the one-time-/day codes have and the seed number. This is done in the same way as programming a user code: Position 198 is for seed and position 199 is for digits.



10. Free locker

The Free locker function can be used for access control, especially for access control where the user often switches.

Function: Key in a code, and if the cabinet is free, it will lock and can only be unlocked with the same code.

The locker reserve time function can be set to between 1-255 minutes. This means that the locker automatically will unlock after a given time. To access this function, please see the provided configuration scheme for the reader under position 09.

Free locker reset

The user position 193 will make a reset of the free locker function. Please see section 5.7 "special positions" in this manual to see line of procedure.

Thank you for choosing Conlan's products.

For further assistance, please contact
Our support service.